







HL21 Headlamp

Fenix HL21 is a high intensity lightweight headlamp designed for outdoor activities, such as hiking and climbing, etc. The multiple brightness levels with a max 90 lumens output can meet your needs of illumination and runtime in various outdoor conditions. In the meanwhile, the compact and lightweight design is suitable for longtime wearing. Therefore, with the waterproofing to IPX-8 Standard and the portable integrated design, HL21 can fascinate you in various conditions.

Technical Parameters

ANSI/FSC	High	Low	Mid
 OUTPUT	90 LUMENS	3 LUMENS	43 LUMENS
 RUNTIME	2h 3min	53h	5h 43min
 DISTANCE	93m		
 INTENSITY	2158cd		
 IMPACT RESISTANT	1.5m		
 WATERPROOF	IPX-8, underwater 2m		
EXTRA FUNCTION	SOS		
ACCESSORIES	Diffuser lens, spare o-ring		

- Uses Cree XP-E LED (R2) with a lifespan of 50,000 hours
- Uses one 1.5V AA (Ni-MH, Alkaline) battery
- 66mm (Length) * 33.7mm (Width) * 48.8mm(Height)

- 41.1-gram weight (excluding batteries)
- Digitally regulated output - maintains constant brightness
- Reverse polarity protection, to protect from improper battery installation
- Push button switch
- Made of high-quality plastic and aluminum alloy
- The aluminum alloy has the premium Type III hard-anodized anti-abrasive finish
- Toughened ultra-clear glass lens with anti-reflective coating

Notice: The above-mentioned parameters (tested by 2500mAh Ni-MH battery in Lab) are approximate and may vary between headlamps, batteries, and environments.

Operation Instruction

Light turning on/off

Depress the button switch to turn the light on/off;

General mode

When turn on the light, it will enter into the general mode automatically. Depress and hold the button switch (for over 1 second), the light can select brightness levels in the order of High→Low→Mid→Cycle;

Mode selection

When the light is on, a fast double depress on the button switch can change the mode between the general mode and the SOS flashing mode.

Battery Specifications

Type	Dimensions	Nominal voltage	Usability	
Ni-MH Battery	AA	1.2V	Recommended	✓
Alkaline Battery	AA	1.5V	Usable	✓
Non-rechargeable Battery (Lithium)	AA	1.5V	Usable	✓
Rechargeable Battery (Li-ion)	14500	3.7V	Banned	✗

Battery Replacement

Unscrew the tail cap (the side without the button switch) to insert the batteries with the cathode side (-) toward the tube bottom, screw the tail cap back on to test.

Usage and Maintenance

- Please don't disassemble the sealed head, doing so can cause damage to the headlamp and will void the warranty.
- High-power headlamp should use battery with high current discharge capability; we suggest using high performance Ni-MH rechargeable battery to increase the runtime of this high intensity flashlight.
- Please use battery of high quality, and take out the battery if you do not use the headlamp for a long time, or the headlamp could be damaged by electrolyte leakage or battery explosion which is

caused by low quality battery.

- The o-ring may be worn out after using for a long time. If it happens, please replace the o-ring with a new one to keep the headlamp properly sealed against water.
- Please clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:

Reason A: The battery needs replacing.

Solution: Replace batteries (Please confirm the correct installation of anode and cathode).

Reason B: The threads, PCB board contact or other contacts are dirty.

Solution: Clean the contact points with an alcohol soaked cotton swab.

If the above methods don't work, please contact the distributors and refer to the warranty policy.

Notice: The routine cleaning video can be watched and downloaded through Fenix official website, please log onto the service channel->“maintenance for light”.

Product Warranty

We will replace products afflicted with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

Warranty Card Registration

We kindly suggest that you register your guarantee card on the official website of Fenixlight Limited. You can get an extra six-month warranty period once you have successfully registered. What's more, you could take part in the lottery of questionnaire at the same time.

Warning

HL21 is a high intensity lighting device and capable of causing eye damage, avoid shining the light directly into the eyes.

FENIXLIGHT LIMITED

Tel: +86-755-29631163/83/93 Fax: +86-755-29631181

<http://www.fenixlight.com>

E-mail: info@fenixlight.com

Address: 8/F, 2nd Building, Dong Fang Ming

Industrial Center, 33rd District, Bao' an,

Shenzhen 518133, China